



P.O. Box 386
2812 N. 9th St.
Canon City, CO 81212
Tel: 719-275-8691
Fax: 719-269-3397
www.SentrySiren.com

E-4®

113 dB*



Specifications:

***113 dB. at 10 ft.**
(adjustable from 83-113 dB)

32 different sounds !!!

Switchable to accept:
9 VDC to 30 VDC

110 VAC or 220 VAC

For those looking for a powerful electronic siren in a compact package, Sentry Siren offers the E-4. This extra high output Siren, 113 db(A) (nominal), is highly effective where the ambient noise level is excessive. The Model E-4 features **Thirty Two distinctive sounds, including ISO certified and country specific warning sounds. All sounds can be obtained from a two wire supply. The E-4 is switchable to accept between **9 to 30 VDC, and 110 VAC, or 220 VAC**. When versatility is a must, the E-4 is at home in a wide range of industrial, office, hotel and many other emergency signaling environments.**

Siren is 3 5/8" Ht. x 3 5/8" Wd. x 2 7/8" Dp. and made of ABS thermoplastic. It has two wire leads and a 1" NPT rigid conduit opening. Mounting hardware not included. Red in color. Can be mounted using supplied base or with optional 4 X 4 Electrical Box and Blank. Sirens draw .015 amps @ 110 VAC, .008 amps @ 220 VAC, .06 amps @ 12 VDC, and .03 amps @ 24 VDC.

Versatility and Power at the Right Price !!!

Sentry Siren, Inc
Model E-4 - Tone Specifications

Sound #	Description
1	Banshee LF Buzz
2	Banshee Fast Sweep
3	Banshee Slow Sweep
4	Banshee Continuous
5	Banshee Fast Sweep (New)
6	Medium Sweep
7	Continuous
8	back up alarm
9	alternate
10	medium sweep
11	alternate
12	Bedlam Buzz
13	Bedlam Fast Sweep
14	Bedlam Slow Sweep
15	Bedlam Continuous
16	Banshee HF Fast Sweep
17	Back up alarm HF
18	Alternate HF
19	Slow Whoop
20	Din Tone
21	French Fire Sound
22	Australian Alert Signal
23	Australian Evacuation Signal
24	US Temporal Tone
25	US Temporal Tone
26	Swedish Tone (Fire)
27	Swedish Tone (All Clear)
28	ISO 8201 LF
29	ISO 8201 HF
30	BT Banshee FP 1063.1
31	BT Banshee FP 1063.1
32	Bell Tone